



American Hakko Products, Inc.

PRODUCT BULLETIN

Bulletin No: PB223

Issue Date: August 22, 2005

Product:

FT-800 Thermal Wire Stripper

Part No:

FT800-01

Comments:

The FT-800 Thermal Wire Stripper will strip a wide variety of wire insulations. The blades can heat up to approximately 800°C (1472°F) and are easy to replace. The FT-800 includes one set of standard blades, notched to fit 18 to 28 AWG wires. Straight blades are available as an accessory. Two lead adjusters are included that will allow repeatable wire strip lengths from 1-38 mm. To extend the life of the blades the FT-800 has a power save mode. When the FT-8001 handpiece is placed in the holder the station enters the power save mode and reduces the blade temperature by approximately 50%. The FT-8001 handpiece has an indicator light that shows when the blade temperature has stabilized.



Specification:

Power Consumption	120V AC / 68W
Temperature range	Approx 200 to 800°C (392 to 1472°F)
Dimensions	120 (W) x 93 (H) x 170 (D) mm (4.7 x 3.7 x 6.7 in.)
Weight (w/o cord)	1.3 kg. (2.9 lbs)
Handpiece cord length	1.3 m (4.3 ft.)
Handpiece length w/o cord)	140 mm (5.5 in.)

For pricing information, please contact your local American Hakko representative or our customer service department at (661) 294-0090.

From...

American Hakko Products, Inc.
 28920 Avenue Williams.
 Valencia, CA 91355
 Tel: (661) 294-0090
 Fax: (661) 294-0096
 www.hakkousa.com
 AHP14 Rev 2000-01

Contents:

Part Number	Part Name
N/A	FT-800 station
FT8001-01	Handpiece
G1-1601	Blade 18-28 AWG
B3077	Lead adjuster A
B3089	Lead adjuster B
B2300	Heat resistant pad
B2017	Hexacon wrench (1.5 mm)

Accessories:

Part Number	Part Name
G1-1602	Straight Blade

List Price:

\$399.97

Available:

September 6, 2005

For pricing information, please contact your local American Hako representative or our customer service department at (661) 294-0090.

From...

American Hako Products, Inc.
28920 Avenue Williams.
Valencia, CA 91355
Tel: (661) 294-0090
Fax: (661) 294-0096
www.hakkousa.com
AHP14 Rev 2000-01